# PR900 Upgrade Guide

## 1. Notes

This upgrade package only supports upgrade from V1.00.12 to V1.01.07 through the network port.


#### 2. upgrade tools

- (1) CPS version: CPS: V3.05.034B3
- (2) Upgrade file: V1.01.07.pack
- (3) IP network

The computer and PR900 can be connected directly through the network cable or through the router. They must be in the same network segment.

#### 3. Upgrade steps

(1) Click on the program in the menu bar, then select and click Remote Upgrade from the drop down box.



(2) Input PR900 IP address



	Service IP 70 . 1 . 91 . 186	
	Service Port 50009	
Choose packag	e D:\PR900\Repeater_V1.01.07\firmware_V1.01.	07\V1
choose packag		
		_
tx_dsp_main_N	clude:PR900.rcdb, UsbBootBios.bin, tx_arm_main.bi I.bin, tx_dsp_main_A.bin, PR900.pic, PR900.carton, ais, ulmage, ubi.img, rx_arm.bin, rx_dsp_main.bin,	n, -
tx_dsp_main_N	l.bin, tx_dsp_main_A.bin, PR900.pic, PR900.carton,	n, -
tx_dsp_main_N	Lbin, tx_dsp_main_A.bin, PR900.pic, PR900.carton, als, ulmage, ubLimg, rx_arm.bin, rx_dsp_main.bin,	
tx_dsp_main_N font.bin, uboot.a	Lbin, tx_dsp_main_A.bin, PR900.pic, PR900.carton, als, ulmage, ubLimg, rx_arm.bin, rx_dsp_main.bin,	

## (3) Choose upgrade package

	Service IP 70	. 1 .	91 . 1	86	
Se	rvice Port 5000	9			
	D:\PR900\Repeat	or 1/1.01/	17) 6	a 1/1 01 0	701/4
Choose package	D. PROUVRepeat	ei_v1.01.	27 111 11199 01	e_v1.01.0	
The PackFile Includ	le:PR900.rcdb, Us				-
font.bin, uboot.ais,			rx_dsp_n	nain.bin,	
			rx_dsp_n	nain bin,	~
font.bin, uboot.ais,	ulmage, ubi.img, i		, rx_dsp_n	nain.bin,	Ŷ
	ulmage, ubi.img, i		.rx_dsp_n	iain.bin,	v
font.bin, uboot.ais,	ulmage, ubi.img, i		.rx_dsp_n	nain.bin,	Ŷ

(4) Click OK button



S	ervice IP 70 . 1 . 91 . 186	
Sen	rice Port 50009	
15	1000000	
Choose package	.\PR900\Repeater_V1.01.07\firmware_V1	.01.07\V1
[]		
The PackFile Include	PR900.rcdb, UsbBootBios.bin, tx_arm_ma	
The PackFile Include x_dsp_main_N.bin,	PR900.rcdb, UsbBootBios.bin, tx_arm_ma x_dsp_main_A.bin, PR900.pic, PR900.can mage, ubl.img, rx_arm.bin, rx_dsp_main.bi	ton,
The PackFile Include x_dsp_main_N.bin,	x_dsp_main_A.bin, PR900.pic, PR900.car	ton,
The PackFile Include tx_dsp_main_N.bin,	x_dsp_main_A.bin, P <b>R</b> 900.pic, PR900.can Image, ubl.img, rx_arm.bin, rx_dsp_main.bi	ton, in,
The PackFile Include x_dsp_main_N.bin, font.bin, uboot.ais, u	x_dsp_main_A.bin, P <b>R</b> 900.pic, PR900.can Image, ubl.img, rx_arm.bin, rx_dsp_main.bi	ton, in,

.....

(5) Wait for the upgrade to complete, PR900 will reboot automatically

Mes Choose p	sage		×	)7.pack
upgrade upgrade upgrade upgrade		rade Done, the y reboot, pleas		^
00%		L	ок	

(6) Upgrade complete.